

An effective method of obtaining an Arc OK signal from a plasma power supply without a CNC port is to mount a reed relay inside a non-conductive tube and wrap and secure three turns of the work lead around the tube. This assembly will now act as a relay that will switch on when current is flowing through the work lead which only occurs when a cutting arc has been established.

